

MZ-200 Small Ozone Generator

Ozone Generator for your vehicle & closets!

The MZ-200 is ideal for removing persistent odors from your vehicle. Use it to keep a room or closet fresh. Satisfaction guaranteed or your money back!



Features

- 750-sq ft Capability
- 200 mg/hr ozone output
- Includes 100-240V AC Adapter
- Includes a 12V DC Car Adapter
- [i]4- Year Warranty[/i]
- Fully Adjustable Output
- Ideal for a small room or closet

Product ID: **MZ-200**
 Lead Time: **1 week**
 Price: **\$255.00**

Replacement / Spare Mica Plates

The MZ-200 has a single mica plate inside. Replacing the mica plate is inexpensive, simple and only requires a screw driver. (Be sure to power down and unplug the unit before opening the chassis.)

	Part	Description	Price	*
44210	MZ-200 Mica Plate	Order this plate as a replacement or spare. Compatible with the MZ-200 ozone generator.	Online Pricing	Buy Online!

Specifications

[b]Generation Method:[/b]	Ultra-high Frequency Corona Discharge
[b]Supply Gas:[/b]	Ambient Air
Max Ozone Output:	200 mg/hr
[b]Controls:[/b]	On/Off Rocker Switch. Fully Variable Control For Ozone Output
[b]Electrical:[/b]	Power brick included, 100-240V AC Adapter & 12VDC Cigarette Lighter Adapter
Fan Size:	16-CFM
[b]Construction:[/b]	High Grade [b]304 Stainless Steel Chassis.[/b] Corona Plate Is Made Of [b]316L Stainless Steel (highest grade) & Muscovite semi-flexible mica[/b] (excellent handling properties).
[b]Maintenance:[/b]	Under normal 24 hr/day use the ozone generator plate should be cleaned every 8 to 10 months using dish soap, water and a tooth brush. Cleaning frequency is highly dependent on the humidity level of the air that the ozone generator receives.
[b]Warranty:[/b]	Four Years
Dimensions:	3 x 5 x 4.5-in (HxWxD) (7.5 x 13 x 11.5-cm)
Weight:	32 oz (1 kg)
Shipping Weight:	64 oz (1.8 kg)