

Ozone Generator for Residential Use

Small shock treat Ozone Generator

Use this portable ozone generator in your home or residence. Just set on floor and let run overnight for quick odor removal! Unit cleans large areas with high flow fan.



Features

- 3,600 mg/hr ozone output
- adjustable output
- four year warranty
- minimal maintenance
- destroys odors permanently!
- high flow 105 CFM fan!

Product ID: **OMZ-3600-HF**
 Stock: **Yes**
 Price: **\$645.00**

Replacement / Spare Mica Plates

The OMZ-3600-HF has ten mica plates inside. Replacing the mica plates is inexpensive, simple, and only requires a screw driver. (Be sure to power down and unplug the unit before opening the chassis.)

*	Part	Description	Price	*
43276	OMZ Mica Plate	Order this plate as a replacement or spare. Compatible with OMZ generators from OMZ-1000 and up. 10% discount for orders of 10 or more.	Online Pricing	Buy Online!

Specifications

Generation method:	Corona discharge
Supply Gas:	Ambient air
Max. ozone output:	3,600 mg/hr
Controls:	On/Off rocker switch. Fully variable output control
Electrical:	120V/60Hz, 60 Watt - 220V/50Hz available
Power Consumption:	60 Watts
Fan Size:	4.5-in diameter - 105 CFM
Construction:	304 stainless steel inner chassis with a high impact extruded PVC cabinet. Corona Plate is made of 316L stainless steel (highest grade) & Muscovite semi-flexible mica (excellent handling properties).
Maintenance:	Under normal 24 hr/day use, the OMZ-3,600-HF ozone generator should be cleaned every 4 to 8 weeks using dish soap, water and a tooth brush. Cleaning frequency is highly dependent on the humidity level.
Warranty:	Four years - complete parts & labor!
Dimensions:	7.5 x 6.5 x 23-in (HxWxD) 19 x 16.5 x 58.5-cm
Weight:	10-lbs (4.5 kg)
Shipping Weight:	12 lbs (5.5-kg)

OMZ Uses



The OMZ-3600-HF has multiple uses since it has a standard 4-in inlet & outlet. Dryer vent hose easily connects to either end. One can push, or pull, ozone from one area to another without constantly recirculating the same air through the machine.